

SCA J99-500 Bill of Material

SCA J99-500 Bill of Material								Rev 1
Item	Qty	Ref	Value	Marking	Description	Manufacturer	Manufacturer's No	Source
1	2	C1, C16	100pF	100	COG Ceramic Capacitor	Kemet	C315C101J1G5TA	Mouser
2	2	C6, C12	680pF	681	COG Ceramic Capacitor	Kemet	C315C681J1G5TA	Mouser
3	1	C2	.1uF	104	X7R Ceramic Capacitor	Panasonic	C320C104K1R5TA	Digi-Key
4	6	C8, C9, C14, C15, C26, C27	470nF	474	Metallized Film Capacitor	Panasonic	ECQ-V1H474JL	Digi-Key
5	6	C4, C5, C10, C11, C19, C23	10uF	106 / 35V	Tantalum Electrolytic Capacitor	Kemet	T350G106K035AT	Mouser
6	2	C108, C109	47uF	47uf 35V	Radial Electrolytic	Panasonic	EEU-FC1H470	Digi-Key
7	2	C24, C25	100uF	100uF 63V	Radial Electrolytic Capacitor	Panasonic	EEU-FC1J101L	Digi-Key
8	1	C102	330uF	330uF 35V or 50V	Radial Electrolytic Capacitor	Panasonic	ECO-S1HA152BA	Mouser
9	2	C104, C105	1000pF/2KV	Suppression Cap	Suppression Cap	Vishay	S102M33Z5UR63L6R	Digi-Key
10	1	L101	4.7uH	Shielded Inductor	Shielded Inductor	Bourns	CM322522-4R7JL	Digi-Key
11	1	R13, R15, R25	10R0	Brown-Black-Black-Gold-Brown	Metal Film Resistor	Xicon	271-10-RC	Mouser
12	1	R19	38R3	Orange-Gray-Orange-Gold-Brown	Metal Film Resistor	Xicon	271-38.3-RC	Mouser
13	2	R9, R18	69R8	Blue-White-Gray-Gold-Brown	Metal Film Resistor	Xicon	271-69.8-RC	Mouser
14	2	R8, R22	127	Brown-Red-Violet-Black-Brown	Metal Film Resistor	Xicon	271-127-RC	Mouser
15	1	R40	150	Brown-Green-Black-Black-Brown	Metal Film Resistor	Xicon	271-150-RC	Mouser
16	2	R11, R21	237	Red-Orange-Violet-Black-Brown	Metal Film Resistor	Xicon	271-237-RC	Mouser
17	2	R10, R20	464	Yellow-Blue-Yellow-Black-Brown	Metal Film Resistor	Xicon	271-464-RC	Mouser
18	1	R4	590	Green-White-Black-Black-Brown	Metal Film Resistor	Xicon	271-590-RC	Mouser
19	1	R30	604	Blue-Black-Yellow-Black-Brown	Metal Film Resistor	Xicon	271-604-RC	Mouser
20	1	R3	750	Violet-Green-Black-Black-Brown	Metal Film Resistor	Xicon	271-750-RC	Mouser
21	1	R23	1K00	Brown-Black-Black-Brown-Brown	Metal Film Resistor	Xicon	271-1K-RC	Mouser
22	1	R5	1K05	Brown-Black-Green-Brown-Brown	Metal Film Resistor	Xicon	271-1.05K-RC	Mouser
23	1	R6	1K82	Brown-Gray-Red-Brown-Brown	Metal Film Resistor	Xicon	271-1.82K-RC	Mouser
24	2	R12, R26	2K00	Red-Black-Black-Brown-Brown	Metal Film Resistor	Xicon	271-2K-RC	Mouser
25	1	R7	3K30	Orange-Orange-Black-Brown-Brown	Metal Film Resistor	Xicon	271-3.3K-RC	Mouser
26	2	R1, R2	6K65	Blue-Blue-Green-Brown-Brown	Metal Film Resistor	Xicon	271-6.65K-RC	Mouser
27	1	R42	10K0	Brown-Black-Black-Red-Brown	Metal Film Resistor	Xicon	271-10K-RC	Mouser
28	1	R14	15K0	Brown-Green-Black-Red-Brown	Metal Film Resistor	Xicon	271-15K-RC	Mouser
29	1	R41	100K	Brown-Black-Black-Orange-Brown	Metal Film Resistor	Xicon	271-100K-RC	Mouser
30	1	R27	200K	Red-Black-Black-Orange-Brown	Metal Film Resistor	Xicon	271-200K-RC	Mouser
31	2	R16, R17	1M00	Brown-Black-Black-Yellow-Brown	Metal Film Resistor	Xicon	271-1.0M-RC	Mouser
32	8	R28, R29, R44 - R46, R48 - R50	2M00	Red-Black-Black-Yellow-Brown	Metal Film Resistor	KOA	MF1/2CC2004F	Mouser
33	1	R24	1K	91A1A-B24-B10L	Panel Control	Bourns	91A1A-B24-B10L	Newark
34	2	R43, R47	10K	Y 103	25-Turn Potentiometer	Bourns	3296Y-1-103LF	Digi-Key
35	7	D1 - D5, D7, D11	1N4002	1N4002	Rectifier Diode	General Semi	1N4002	Digi-Key
36	1	Q1	MPSA06	MPSA06	NPN Bipolar Transistor	Fairchild	MPSA06	Mouser
38	2	U1, U2	990C+ or SC90	990C+ or SC90	Discrete Op-Amp	John Hardy or SCA	990C+ or SC90	SCA
39	1	U3	LT1013	LT1013CP	Dual Op-Amp	Texas Instruments	LT1013CP	Digi-Key
40	1	U4	PDQE10-Q24-D24-D	DC-DC Converter	DC-DC Converter	CUI	PDQE10-Q24-D24-D	Digi-Key
41	1	U6	LM78L12	LM78L12	Voltage Regulator, Positive	National	LM78L12ACZ	Digi-Key
42	1	U7	LM79L12	LM79L12	Voltage Regulator, Negative	National	LM320LZ-12	Digi-Key
43	1	J5			2 Position Header	Molex	22-28-4020	Digi-Key
44	2	J6, J7			3 Position Header	Molex	22-28-4030	Digi-Key
45	3				Shorting Jumper	Sullins	STC02SYAN	Digi-Key
46	1	SW1		71BDF30-03-1-AJS	Rotary Switch	Grayhill	71BDF30-03-1-AJS	Grayhill
47	1	SW2		100A WSP1	Single-Pole Toggle Switch	E-Switch	100AWSP1T2B4M7RE	Mouser
48	2	SW3, SW4		100A WDP1	Double-Pole Toggle Switch	E-Switch	100AWDP1T2B4M7RE	Digi-Key
49	1	T1		LL1538XL	Input Transformer	Lundahl	LL1538XL	Lundahl
50	1	T2		CMOB-2H	Output Transformer	CineMag	CMOB-2H	Cinemag
51	12	U1, U2			PCB Socket	Mil-Max	0328-0-15-01-3427100	Digi-Key
52	2				Fluted Knob	Cosmo	39-7747-001-00-3-10	Cosmo
53	1	HARDWARE		500 Tray				SCA
54	1	HARDWARE		500 Cover				SCA
55	1	HARDWARE		B16-500 Faceplate				SCA
56	8	HARDWARE	#4-40 x 1/8"	Flat head machine screw				MISC
57	2	HARDWARE	#4-40 x 1"	Flat head machine screw				MISC
58	4	HARDWARE	#4-40	Kepps nut				MISC
59	4	HARDWARE	#4-40 x 3/16"	HEX STANDOFF #4-40 ALUM 3/16"				MISC
60	2	HARDWARE		1/8" Nylon spacer				MISC
61	4	HARDWARE	#4-40 x 1-1/16"	1/4 HEX 1-1/16" LENGTH Spacer				MISC
62	1				PCB	SCA		SCA